# **Technical Bulletin**

### AN-110-SW Local GUI Firmware Update Instructions



## Introduction

AN-110 series switches have a basic local interface where a firmware update may be performed. We suggest using OvrC to update firmware if possible.

## Accessing the Local Interface

- 1. Find the IP address issued to the device by looking in the router or using a network scanning tool.
- 2. Enter the IP address into a web browser.
- 3. Log in using the default credentials.

Default Login		http://jrw732.arakr password. Your connection to	http://jrw732.araknisdns.com:5431 requires a username ar aassword. /our connection to this site is not private.			
User Name	araknis	User Name:	Jser Name: araknis			
Password	araknis	Password:	******			
				Log In	Cancel	

Authentication Required

#### **Firmware Upgrade Instructions**

1. Navigate to the Tools > Firmware Upgrade menu and click **Enter Loader Mode**. Click **Okay** if the dialog window appears.

User Account  Contemporate  Firmware Upgrade  Factory Default	Firmware Upgrade Enter loader mode to upgrade firmware. Enter Loader Mode
	jrw732.araknisdns.com:5431 says: × Enter Loader Mode? Prevent this page from creating additional dialogs. OK Cancel

2. Click HTTP Firmware Upgrade in the left menu.

Firmware Upgrade     HTTP Firmware Upgrade     Exit Loader Mode	araknis
	Loader Mode Firmware upgrade mode. Please upload your image by HTTP

# **Technical Bulletin**

## AN-110-SW Local GUI Firmware Update Instructions



3. Click **Choose File** to select the firmware file, then click **Upgrade** to begin the upgrade process.

Firmware Upgrade HTTP Firmware Upgrade Exit Loader Mode	araknis
	Firmware Upgrade Choose File No file chosen Upgrade

4. The switch will restart when the update completes, and you will be prompted to log back in. Settings will be retained from the previous firmware version.

# **Contacting Technical Support**

Phone: (866) 838-5052

Email: support@araknisnetworks.com