

30 in. Three-Channel Soundbar with 3 in. Woofers



#### **DESCRIPTION**

Flat Panels have a reason to celebrate. The Episode 300 Series Sound bar offers an incredible sound system without the clutter of a bunch of speakers, designed to fit perfectly either mounted underneath or placed below a flat panel TV. A single unit consisting of left, center, and right channels makes this speaker ideal for bedroom or living room applications.

# **SPECIFICATIONS**

Four 3" PP Injection Cones w/ High Temp Voice Coil Four 3" Passive Radiators
Three 3/4" Silk Dome, Neo-Magnet, ferrofluid cooled Tweeters
80 W RMS, 200 W Peak
8 Ohms
115 Hz - 22 kHz
88 dB
2.5 kHz
3 sets of Gold-Plated Push Terminals
10 lbs.
Acoustically Transparent Cloth
30.2 L x 4.5 H x 2.83 D

# **Premium Components:**

Features silk dome tweeters and polypropylene injection woofers built with Nomex™ Spiders and high-temperature voice-coils. Use of neodymium magnets delivers the punch and performance while minimizing the speaker depth off the wall.

### **Low-Profile Design**

A perfect balance of aesthetics and acoustical performance results in a thin profile ideal for today's slim-model TV's and mounts, with an aluminum cabinet that is stronger than wood or plastic and offers a streamlined look with a slim 2.75" depth.

# **Hidden IR Control:**

A discreet knock-out behind the grille makes this speaker compatible with any IR control system, without the unsightly look of stick-on receivers.

# **Flexible Placement Options:**

Whether mounting directly on a wall, to the TV mount, or on top of a console, the 300 Series Soundbar offers a wall-mount bracket, universal TV mounting bracket, and a kickstand for on-cabinet placement.

#### Lifetime Limited Warranty

All Episode Speakers have a Lifetime Limited Warranty. This warranty includes parts and labor repairs on all components found to be defective in material or workmanship under normal conditions of use. This warranty shall not apply to products which have been abused, modified or disassembled. Products to be repaired under this warranty must be returned to SnapAV or a designated service center with prior notification and an assigned return authorization number (RA).